Product data sheet



SC-11-2201-0001-99

SmartCell Wireless Control Panel (No Comms Module) (24V) - English (International)

SmartCell overview

SmartCell has been designed as a complete wireless fire detection system to protect people and property. The system incorporates separate information zones which allow input devices to be configured in multiple configurations, providing maximum flexibility to the user and designer.

A SmartCell system can support up to 64 wireless devices consisting of 32 fire devices and 32 information devices.

Communication between devices and the control panel is bidirectional and operates in the European harmonised 868MHz frequency band.

With significant time saving against conventional and addressable fire system installations, no cables, no mess and no inconvenience to everyday business, SmartCell is perfect for all small to medium sized fire system installations.



Details

- · Fully wireless
- Quick and easy to install
- · Compact enclosure
- 80 character OLED display
- Accommodates internal communications card for SmartCell Services connection
- 230 VAC version also available

SC-11-2201-0001-99

SmartCell Wireless Control Panel (No Comms Module) (24V) - English (International)

Technical specifications

General	
User interface	16 zone indicators
Maximum system	1 to 32
capacity (device count)	
Electrical	
Power supply type	24 VDC
Operating voltage	19.2 to 28.8 VDC
Current consumption	0.035 A (quiescent and alarm current)
Zone	
Maximum zone capacity	up to 16
Physical	
Form factor	Compact
Physical dimensions	275 x 220 x 80 mm (W x H x D)
Net weight	1.45 kg
Mounting type	Surface mount
Cable entries	4 x 100 mm (bottom) / 4 x 100 mm (back)
Environmental	
Operating temperature	-5°C to +45°C
Storage temperature	0°C to +30°C
Relative humidity	95% noncondensing max.
Environment	Indoor
IP rating	IP30
Standards & regulation	
Compliancy	CE
Certification	CPR
Standards	EN54-2
	EN54-13
	EN54-25
Wireless signalling	
Operating frequency	868 to 870 MHz
Output transmitter	14 dBm max. / 25 mW
power	

